

Features

- 300MHz -3dB bandwidth
- 4mA supply current (per amplifier)
- Single and dual supply operation, from 5V to 10V
- Single (EL5193C) and triple (EL5393C) available
- High speed, 1GHz product available (EL5191C)
- High speed, 6mA, 600MHz product available (EL5192C, EL5292C, and EL5392C)

Applications

- Battery-powered Equipment
- Hand-held, Portable Devices
- Video Amplifiers
- Cable Drivers
- RGB Amplifiers
- Test Equipment
- Instrumentation
- Current to Voltage Converters

Ordering Information

| Part No | Package | Tape & Reel | Outline # |
|--------------|----------|-------------|-----------|
| EL5293CS | 8-Pin SO | - | MDP0027 |
| EL5293CS-T7 | 8-Pin SO | 7" | MDP0027 |
| EL5293CS-T13 | 8-Pin SO | 13" | MDP0027 |


General Description

The EL5293C is a dual current feedback amplifier with a bandwidth of 300MHz. This makes these amplifiers ideal for today's high speed video and monitor applications.

With a supply current of just 4mA per amplifier and the ability to run from a single supply voltage from 5V to 10V, these amplifiers are also ideal for hand held, portable or battery powered equipment.

The EL5293C is offered in the industry standard 8-pin SO. The EL5293C operates over the industrial temperature range of -40°C to +85°C.

Pin Configurations



Note: All information contained in this data sheet has been carefully checked and is believed to be accurate as of the date of publication; however, this data sheet cannot be a "controlled document". Current revisions, if any, to these specifications are maintained at the factory and are available upon your request. We recommend checking the revision level before finalization of your design documentation.

EL5293C

Dual 300MHz Current Feedback Amplifier

Absolute Maximum Ratings (T_A = 25°C)

Values beyond absolute maximum ratings can cause the device to be prematurely damaged. Absolute maximum ratings are stress ratings only and functional device operation is not implied.

Supply Voltage between V_{S+} and V_{S-} 11V
Maximum Continuous Output Current 50mA

Operating Junction Temperature 125°C
Power Dissipation See Curves
Pin Voltages V_{S-} - 0.5V to V_{S+} +0.5V
Storage Temperature -65°C to +150°C
Operating Temperature -40°C to +85°C

Important Note:

All parameters having Min/Max specifications are guaranteed. Typ values are for information purposes only. Unless otherwise noted, all tests are at the specified temperature and are pulsed tests, therefore: T_J = T_C = T_A.

Electrical Characteristics


V_{S+} = +5V, V_{S-} = -5V, R_F = 750Ω for A_V = 1, R_F = 375Ω for A_V = 2, R_L = 150Ω, T_A = 25°C unless otherwise specified.

| Parameter | Description | Conditions | Min | Typ | Max | Unit |
|--------------------------------|--|--|------|------|-----|--------|
| AC Performance | | | | | | |
| BW | -3dB Bandwidth | A _V = +1 | | 300 | | MHz |
| | | A _V = +2 | | 200 | | MHz |
| BW1 | 0.1dB Bandwidth | | | 20 | | MHz |
| SR | Slew Rate | V _O = -2.5V to +2.5V, A _V = +2 | 2000 | 2200 | | V/μs |
| t _s | 0.1% Settling Time | V _{OUT} = -2.5V to +2.5V, A _V = -1 | | 12 | | ns |
| C _S | Channel Separation | f = 5MHz | | 60 | | dB |
| e _n | Input Voltage Noise | | | 4.4 | | nV/√Hz |
| i _{n-} | IN- input current noise | | | 17 | | pA/√Hz |
| i _{n+} | IN+ input current noise | | | 50 | | pA/√Hz |
| dG | Differential Gain Error ^[1] | A _V = +2 | | 0.03 | | % |
| dP | Differential Phase Error ^[1] | A _V = +2 | | 0.04 | | ° |
| DC Performance | | | | | | |
| V _{OS} | Offset Voltage | | -10 | 1 | 10 | mV |
| T _C V _{OS} | Input Offset Voltage Temperature Coefficient | Measured from T _{MIN} to T _{MAX} | | 5 | | μV/°C |
| R _{OL} | Transimpedance | | 300 | 600 | | kΩ |
| Input Characteristics | | | | | | |
| CMIR | Common Mode Input Range | | ±3 | ±3.3 | | V |
| CMRR | Common Mode Rejection Ratio | | 42 | 50 | | dB |
| +I _{IN} | + Input Current | | -60 | 1 | 60 | μA |
| -I _{IN} | - Input Current | | -35 | 1 | 35 | μA |
| R _{IN} | Input Resistance | | | 45 | | kΩ |
| C _{IN} | Input Capacitance | | | 0.5 | | pF |
| Output Characteristics | | | | | | |
| V _O | Output Voltage Swing | R _L = 150Ω to GND | ±3.4 | ±3.7 | | V |
| | | R _L = 1kΩ to GND | ±3.8 | ±4.0 | | V |
| I _{OUT} | Output Current | R _L = 10Ω to GND | 95 | 120 | | mA |
| Supply | | | | | | |
| I _{SON} | Supply Current - Enabled (per amplifier) | No Load, V _{IN} = 0V | 3 | 4 | 5 | mA |
| PSRR | Power Supply Rejection Ratio | DC, V _S = ±4.75V to ±5.25V | 55 | 75 | | dB |
| -IPSR | - Input Current Power Supply Rejection | DC, V _S = ±4.75V to ±5.25V | -2 | | 2 | μA/V |


1. Standard NTSC test, AC signal amplitude = 286mV_{p-p}, f = 3.58MHz

Typical Performance Curves


Non-Inverting Frequency Response (Gain)




Non-Inverting Frequency Response (Phase)




Inverting Frequency Response (Gain)




Inverting Frequency Response (Phase)



Frequency Response for Various C_{IN}



Frequency Response for Various R_L




EL5293C


Dual 300MHz Current Feedback Amplifier

Typical Performance Curves


Frequency Response for Various C_L




Frequency Response for Various R_F




Group Delay vs Frequency




Frequency Response for Various Common-mode Input Voltages









Transimpedance (ROL) vs Frequency



PSRR and CMRR vs Frequency



Typical Performance Curves




EL5293C


Dual 300MHz Current Feedback Amplifier

Typical Performance Curves


Peaking vs Temperature




Voltage and Current Noise vs Frequency




Closed Loop Output Impedance vs Frequency




Supply Current vs Supply Voltage









2nd and 3rd Harmonic Distortion vs Frequency



Two-tone 3rd Order Input Referred Intermodulation Intercept (IIP3)



Typical Performance Curves




EL5293C


Dual 300MHz Current Feedback Amplifier

Typical Performance Curves


Settling Time vs Settling Accuracy




Transimpedance (RoI) vs Temperature




PSRR and CMRR vs Temperature




ICMR and IPSR vs Temperature



Offset Voltage vs Temperature




Input Current vs Temperature




Typical Performance Curves


Positive Input Resistance vs Temperature




Supply Current vs Temperature




Positive Output Swing vs Temperature for Various Loads




Negative Output Swing vs Temperature for Various Loads



Output Current vs Temperature



Slew Rate vs Temperature




EL5293C

Dual 300MHz Current Feedback Amplifier


Typical Performance Curves

Channel-to-Channel Isolation vs Frequency



Package Power Dissipation vs Ambient Temp.

JEDEC JESD51-3 Low Effective Thermal Conductivity Test Board



Pin Descriptions

| EL5293C 8-Pin SO | Pin Name | Function | Equivalent Circuit |
|---------------------|-----------------|--------------------------------|---|
| 1 | OUTA | Output, channel A | <p style="text-align: center;">Circuit 1</p> |
| 2 | INA- | Inverting input, channel A | <p style="text-align: center;">Circuit2</p> |
| 3 | INA+ | Non-inverting input, channel A | (See circuit 2) |
| 4 | V _{S-} | Negative supply | |
| 5 | INB+ | Non-inverting input, channel B | (See circuit 2) |
| 6 | INB- | Inverting input, channel B | (See circuit 2) |
| 7 | OUTB | Output, channel B | (See circuit 1) |
| 8 | V _{S+} | Positive supply | |

EL5293C

Dual 300MHz Current Feedback Amplifier

Applications Information

Product Description

The EL5293C is a current-feedback operational amplifier that offers a wide -3dB bandwidth of 300MHz and a low supply current of 4mA per amplifier. The EL5293C works with supply voltages ranging from a single 5V to 10V and they are also capable of swinging to within 1V of either supply on the output. Because of their current-feedback topology, the EL5293C does not have the normal gain-bandwidth product associated with voltage-feedback operational amplifiers. Instead, its -3dB bandwidth to remain relatively constant as closed-loop gain is increased. This combination of high bandwidth and low power, together with aggressive pricing make the EL5293C the ideal choice for many low-power/high-bandwidth applications such as portable, handheld, or battery-powered equipment.

For varying bandwidth needs, consider the EL5191C with 1GHz on a 9mA supply current or the EL5192C with 600MHz on a 6mA supply current. Versions include single, dual, and triple amp packages with 5-pin SOT23, 16-pin QSOP, and 8-pin or 16-pin SO outlines.

Power Supply Bypassing and Printed Circuit Board Layout

As with any high frequency device, good printed circuit board layout is necessary for optimum performance. Low impedance ground plane construction is essential. Surface mount components are recommended, but if leaded components are used, lead lengths should be as short as possible. The power supply pins must be well bypassed to reduce the risk of oscillation. The combination of a 4.7 μ F tantalum capacitor in parallel with a 0.01 μ F capacitor has been shown to work well when placed at each supply pin.

For good AC performance, parasitic capacitance should be kept to a minimum, especially at the inverting input. (See the Capacitance at the Inverting Input section) Even when ground plane construction is used, it should be removed from the area near the inverting input to minimize any stray capacitance at that node. Carbon or Metal-Film resistors are acceptable with the Metal-Film resistors giving slightly less peaking and bandwidth because of additional series inductance. Use of sockets,

particularly for the SO package, should be avoided if possible. Sockets add parasitic inductance and capacitance which will result in additional peaking and overshoot.

Capacitance at the Inverting Input

Any manufacturer's high-speed voltage- or current-feedback amplifier can be affected by stray capacitance at the inverting input. For inverting gains, this parasitic capacitance has little effect because the inverting input is a virtual ground, but for non-inverting gains, this capacitance (in conjunction with the feedback and gain resistors) creates a pole in the feedback path of the amplifier. This pole, if low enough in frequency, has the same destabilizing effect as a zero in the forward open-loop response. The use of large-value feedback and gain resistors exacerbates the problem by further lowering the pole frequency (increasing the possibility of oscillation.)

The EL5293C has been optimized with a 475 Ω feedback resistor. With the high bandwidth of these amplifiers, these resistor values might cause stability problems when combined with parasitic capacitance, thus ground plane is not recommended around the inverting input pin of the amplifier.

Feedback Resistor Values

The EL5293C has been designed and specified at a gain of +2 with R_F approximately 500 Ω . This value of feedback resistor gives 200MHz of -3dB bandwidth at $A_V=2$ with 2dB of peaking. With $A_V=-2$, an R_F of approximately 500 Ω gives 175MHz of bandwidth with 0.2dB of peaking. Since the EL5293C is a current-feedback amplifier, it is also possible to change the value of R_F to get more bandwidth. As seen in the curve of Frequency Response for Various R_F and R_G , bandwidth and peaking can be easily modified by varying the value of the feedback resistor.

Because the EL5293C is a current-feedback amplifier, its gain-bandwidth product is not a constant for different closed-loop gains. This feature actually allows the EL5293C to maintain about the same -3dB bandwidth. As gain is increased, bandwidth decreases slightly while

stability increases. Since the loop stability is improving with higher closed-loop gains, it becomes possible to reduce the value of R_F below the specified 475Ω and still retain stability, resulting in only a slight loss of bandwidth with increased closed-loop gain.

Supply Voltage Range and Single-Supply Operation

The EL5293C has been designed to operate with supply voltages having a span of greater than 5V and less than 10V. In practical terms, this means that the EL5293C will operate on dual supplies ranging from $\pm 2.5V$ to $\pm 5V$. With single-supply, the EL5293C will operate from 5V to 10V.

As supply voltages continue to decrease, it becomes necessary to provide input and output voltage ranges that can get as close as possible to the supply voltages. The EL5293C has an input range which extends to within 2V of either supply. So, for example, on +5V supplies, the EL5293C has an input range which spans $\pm 3V$. The output range of the EL5293C is also quite large, extending to within 1V of the supply rail. On a $\pm 5V$ supply, the output is therefore capable of swinging from -4V to +4V. Single-supply output range is larger because of the increased negative swing due to the external pull-down resistor to ground.

Video Performance

For good video performance, an amplifier is required to maintain the same output impedance and the same frequency response as DC levels are changed at the output. This is especially difficult when driving a standard video load of 150Ω , because of the change in output current with DC level. Previously, good differential gain could only be achieved by running high idle currents through the output transistors (to reduce variations in output impedance.) These currents were typically comparable to the entire 4mA supply current of each EL5293C amplifier. Special circuitry has been incorporated in the EL5293C to reduce the variation of output impedance with current output. This results in dG and dP specifications of 0.03% and 0.04°, while driving 150Ω at a gain of 2.

Video performance has also been measured with a 500Ω load at a gain of +1. Under these conditions, the EL5293C has dG and dP specifications of 0.03% and 0.04°.

Output Drive Capability

In spite of its low 4mA of supply current, the EL5293C is capable of providing a minimum of $\pm 95mA$ of output current. With a minimum of $\pm 95mA$ of output drive, the EL5293C is capable of driving 50Ω loads to both rails, making it an excellent choice for driving isolation transformers in telecommunications applications.

Driving Cables and Capacitive Loads

When used as a cable driver, double termination is always recommended for reflection-free performance. For those applications, the back-termination series resistor will decouple the EL5293C from the cable and allow extensive capacitive drive. However, other applications may have high capacitive loads without a back-termination resistor. In these applications, a small series resistor (usually between 5Ω and 50Ω) can be placed in series with the output to eliminate most peaking. The gain resistor (R_G) can then be chosen to make up for any gain loss which may be created by this additional resistor at the output. In many cases it is also possible to simply increase the value of the feedback resistor (R_F) to reduce the peaking.

Current Limiting

The EL5293C has no internal current-limiting circuitry. If the output is shorted, it is possible to exceed the Absolute Maximum Rating for output current or power dissipation, potentially resulting in the destruction of the device.

Power Dissipation

With the high output drive capability of the EL5293C, it is possible to exceed the $125^\circ C$ Absolute Maximum junction temperature under certain very high load current conditions. Generally speaking when R_L falls below about 25Ω , it is important to calculate the maximum junction temperature (T_{JMAX}) for the application to determine if power supply voltages, load conditions, or package type need to be modified for the EL5293C to

EL5293C

Dual 300MHz Current Feedback Amplifier

remain in the safe operating area. These parameters are calculated as follows:

$$T_{JMAX} = T_{MAX} + (\theta_{JA} \times n \times PD_{MAX})$$

where:

T_{MAX} = Maximum Ambient Temperature

θ_{JA} = Thermal Resistance of the Package

n = Number of Amplifiers in the Package

PD_{MAX} = Maximum Power Dissipation of Each Amplifier in the Package

PD_{MAX} for each amplifier can be calculated as follows:

$$PD_{MAX} = (2 \times V_S \times I_{SMAX}) + \left[(V_S - V_{OUTMAX}) \times \frac{V_{OUTMAX}}{R_L} \right]$$

where:

V_S = Supply Voltage

I_{SMAX} = Maximum Supply Current of 1A

V_{OUTMAX} = Maximum Output Voltage (Required)

R_L = Load Resistance

EL5293C

Dual 300MHz Current Feedback Amplifier

General Disclaimer

Specifications contained in this data sheet are in effect as of the publication date shown. Elantec, Inc. reserves the right to make changes in the circuitry or specifications contained herein at any time without notice. Elantec, Inc. assumes no responsibility for the use of any circuits described herein and makes no representations that they are free from patent infringement.

élantec

HIGH PERFORMANCE ANALOG INTEGRATED CIRCUITS

Elantec Semiconductor, Inc.

675 Trade Zone Blvd.

Milpitas, CA 95035

Telephone: (408) 945-1323

(888) ELANTEC

Fax: (408) 945-9305

European Office: +44-118-977-6020

Japan Technical Center: +81-45-682-5820

WARNING - Life Support Policy

Elantec, Inc. products are not authorized for and should not be used within Life Support Systems without the specific written consent of Elantec, Inc. Life Support systems are equipment intended to support or sustain life and whose failure to perform when properly used in accordance with instructions provided can be reasonably expected to result in significant personal injury or death. Users contemplating application of Elantec, Inc. Products in Life Support Systems are requested to contact Elantec, Inc. factory headquarters to establish suitable terms & conditions for these applications. Elantec, Inc.'s warranty is limited to replacement of defective components and does not cover injury to persons or property or other consequential damages.